

# Flush Light Fitting

## INSTRUCTION MANUAL

### Safety Warnings

- This product is only suitable for connection to a 240V~50Hz supply in accordance with current IEE wiring regulations. It should be installed in accordance with local building regulations and is for domestic indoor use only. It is not suitable for a bathroom location.
- Before installing your light fitting always switch off the mains supply and remove the appropriate fuse or switch off the appropriate circuit breaker before commencing installation.
- This is a Class I product, and **must** be connected to Earth. The terminal blocks are supplied according to requirements of the fitting.
- Never fit bulbs of a higher wattage than those specified on the label, as these may damage the fitting.
- This product contains delicate parts – be careful during handling and maintenance to avoid breakage. Spare parts are available - Please check with your retailer or call 0333 00 333 08.
- If you are in any doubt about your competence please consult a qualified electrician.
- If any modification is made it will invalidate the warranty and may render the product unsafe.

### Care Information

Allow 10 minutes to cool before replacing, adjusting or cleaning.  
Clean with a dry cloth only. Do not use liquid or abrasive cleaners on this product.

### Assembly/ User Instructions

#### Before you start

Please read these instructions carefully before fitting and retain for reference. Check the packaging and make sure that you have all the required parts. Follow each assembly step in order to prevent incorrect assembly. Ensure that the product is fully assembled as illustrated before use.

#### The Light pack contains:

Light fitting, and terminal connection block(s).  
Fixing pack, including hex key.  
5x glass shades

#### The following tools may be required:


Selection of cross and flat head screwdrivers.  
Electric drill and assorted drill bits.  
Wire strippers.  
Electrical insulation tape.

**These assembly diagrams are intended as a guide – if in doubt consult a qualified electrician.**

1. Decide on the position of the light fitting, or remove existing light fitting. Note the position of the electrical connections. Ensure there is a solid mounting surface, preferably a wooden joist or joist bridge to support the weight of the light fitting.
2. To reduce packaging, this product is shipped with the arms folded. Refer to Diagram A: Before assembling the top and bottom pieces, turn the tubes anticlockwise 5 times (Turning the tubes anticlockwise first ensures that the cable will straighten when the tubes are fully assembled). Screw the stem into the main lamp section (1), being aware of cross-threading, and ensuring the cable is not trapped or damaged. Then twist the lower set of arms to make the cross-form as shown, and secured with the hex key and grub screw (2).
3. Remove the two side screws (6) and retain for re-use. Use the fixing bracket (3) as a template to mark the screw holes. Make the screw holes and secure to the ceiling with appropriate screw fixings (4).
4. Support your fitting and connect the house wiring to the terminal block (5) – see expanded wiring details below.  
**NOTE: This is a Class I fitting and must be earthed.** The 4th terminal block connector is used for the “loop” wires of the “Ring Circuit”. There may be more than one set of cables in the “loop” connections. If there is a “Ring Circuit” and you do not understand the connections you must consult an electrician.
5. Secure the ceiling cup over the bracket by using the screws (6) removed in Point 3.
6. Fit the bulbs (7), being careful not to touch it with your bare hands - use a cloth or gloves. **NOTE: Never fit bulbs of a higher wattage than those specified on the label (as these may cause overheating and damage the fitting).**

# Assembly/ User Instructions Continued

7. Screw the glass shades (8) over the lampholders. **Do not to overtighten**, as the glass shades are delicate.
8. Turn on the power and test.



- EN Scan QR code for multi-language
- FR Scannez le code QR pour plusieurs langues
- ES Escanee el código QR para varios idiomas
- PL Zeskanuj kod QR dla wielu języków
- DE Scannen Sie den QR-Code nach mehreren Sprachen
- IT Scansiona il codice QR per multilingua